

BE Lite Mesh System



WiFi Everywhere in Your Home

Roamii WiFi 7 Mesh System brings fast and reliable WiFi coverage to each corner of your home, allowing you to enjoy online gaming and streaming wherever you are. Simple steps and an intuitive UI make setup a breeze. Advanced mesh technology allows users to roam from the front door to the backyard while connected on a unified network. Roamii BE Lite comes with MSI FortiSecu powered by Trend MicroTM, protecting your smart home by automatically detecting and blocking cyber threats.

Key Features



WiFi 7

The latest WiFi standard featuring MLO, 4K-QAM and MU-MIMO



Dual-band 3.6Gbps

2882 Mbps at 5 GHz and 688 Mbps at 2.4 GHz



Roamii whole home WiFi

Build a unified home network with up to 5,800 sq ft of coverage, supporting 120+ devices.



MLO

Provides multiple band streams to a single device, boosting throughput and reducing latency for a faster and more reliable connection.



FortiSecu

24/7 security protection, parental controls and separated networks



Up and running in minutes

Setup and manage your home network with Roamii app



2.5Gbps Ethernet port

One 2.5Gbps Ethernet port and two 1Gbps Ethernet ports



Wall-mounting kit included

Place Roamii on desktop or mount it on wall as you desire



PHYSICAL INTERFACE







SPECIFICATIONS

Technical Specifications

WiFi standards

WiFi 7 and back forward compatible

- 5 GHz: IEEE 802.11be/ax/ac/n/a
- 2.4 GHz: IEEE 802.11be/ax/n/b/g

WiFi speed

- 2.4GHz BE: Up to 688 Mbps 2x2 4K-QAM
- 5GHz BE: Up to 2882 Mbps 2x2 4k-QAM 20/40/80/160MHz

WiFi features

- Multi-Link operation (MLO)
- Adaptive Puncturing
- MU-MIMO
- **OFDMA**
- 4K-QAM
- Multi-RUs
- Beamforming
- Guest WiFi/ Multiple SSID
- **WPS**

Security

- FortiSecu powered by Trend MicroTM
 - Network security
- Parental controls
- Guest network isolation
- WPA-PSK, WPA2-PSK, WPA3-PSK

VPN

Open VPN Server

Mesh

- Wireless Backhaul
- 802.11k/v/r
- Band Steerina
- AP Steering
- Auto RE configuration
- MLO Backhaul links†
- Backhaul quality LED indicator

Wired interface

- 2.5G Ethernet port x1
- Gigabit Ethernet port x2

Buttons

- Sync button
- Reset button

Processor

Quad Core 1.5GHz

Memory

- RAM 2GB
- Flash 256MB

Management interface

- App (IOS and Android)
- Web GUI

Operation mode

- Router mode
- AP mode

Physical Specifications

Dimensions

118.5 x 108 x 238 mm/ 4.7 x 4.3 x 9.4 inch

585 g / 1.3 lb (per unit)

Power rating

12V/1.5A

Package Contents

Roamii BE Lite(2-pack)

MRBE50 x 2 Power adapter x2 Wall-mount kit x2 Ethernet cable x1 Quick start guide x1

Roamii BE Lite(1-pack)

MRBE50 x 1 Power adapter x1 Wall-mount kit x1 Ethernet cable x1 Quick start guide x1

MLO backhaul will be available with a firmware update in Q1 2025

Maximum wireless signal rate derived from IEEE 802.11 specifications. Actual data throughput and wireless coverage will vary and lowered by network conditions and environmental factors, including volume and density of network traffic, obstacles and building construction.

Use of Wi-Fi 7 (802.11be), Wi-Fi 6 (802.11ax), and features including MLO, 4K-QAM, Multi-RUs, OFDMA, MU-MIMO, 160/240/320MHz-Channel require both router and client to support the corresponding features.

The 160/240/320 MHz bandwidth may be unavailable in some regions/countries due to local regulatory restrictions.

All brand names are registered trademarks of their respective owners. 2024 Micro-Star Int'l Co.Ltd. MSI is a registered trademark of